

# CM-SD825

DIESEL GENERATOR SET / OPEN + SILENT



OPEN SET



SILENT SET

**825** kVA

STANDBY POWER

**750** kVA

PRIME POWER

**60** Hz

FREQUENCY

**480/277** V

VOLTAGE

**SDEC 6KTAA25-G32.1**

3 phase · 0.8 PF · 1800 rpm

## CONFIGURATION COMPARISON

| Configuration | Dimensions (L × W × H) | Dry weight | Fuel tank |
|---------------|------------------------|------------|-----------|
| Open set      | 4320 × 2180 × 2250 mm  | 6320 kg    | 1100 L    |
| Silent set    | 4958 × 2100 × 2537 mm  | 9150 kg    | 1000 L    |

Performance, engine, alternator and controller data are common to both configurations.

# GENERAL CHARACTERISTICS

CM-SD825 · 60 Hz · 3 Phase

## RATED PERFORMANCE

|                        |               |
|------------------------|---------------|
| Standby Power (kVA)    | 825           |
| Standby Power (kW)     | 660           |
| Prime Power (kVA)      | 750           |
| Prime Power (kW)       | 600           |
| Power Factor (Cos Phi) | 0.8           |
| Diesel Engine          | 6KTAA25-G32.1 |
| Frequency (Hz)         | 60            |
| Rated Speed (rpm)      | 1800          |
| Phase                  | 3             |
| Standard Voltage (V)   | 480/277       |

## POWER DEFINITIONS

### STANDBY POWER (ESP)

Available for supplying emergency power during a utility interruption. The stated rating follows ISO 8528-1; overload is not permitted.

### PRIME POWER (PRP)

Available for an unlimited number of annual operating hours in variable-load applications, in accordance with ISO 8528-1.

### TERMS OF USE

Nominal power is stated at 25 °C inlet-air temperature, 100 kPa barometric pressure (100 m A.S.L.) and 30% relative humidity.

## RATED OUTPUT CURRENT BY VOLTAGE

| Rated voltage | Standby current (825 kVA) | Prime current (750 kVA) |
|---------------|---------------------------|-------------------------|
| 480/277 V     | 992.3 A                   | 902.1 A                 |
| 220/127 V     | 2165.1 A                  | 1968.2 A                |
| 440/254 V     | 1082.5 A                  | 984.1 A                 |

# ENGINE DATA

## SDEC 6KTAA25-G32.1

### GENERAL ENGINE DATA

|                           |                                                     |
|---------------------------|-----------------------------------------------------|
| Engine brand              | /                                                   |
| Engine model              | <b>6KTAA25-G32.1</b>                                |
| Engine type               | <b>4-stroke diesel</b>                              |
| Governor type             | <b>ECU</b>                                          |
| Injection type            | <b>Direct</b>                                       |
| Aspiration type           | <b>Turbocharged with<br/>air-to-air intercooled</b> |
| Cylinders and arrangement | <b>6-L</b>                                          |

### FUEL CONSUMPTION

|               |                |
|---------------|----------------|
| 100% load ESP | <b>186 L/h</b> |
| 100% load PRP | <b>168 L/h</b> |
| 75% load PRP  | <b>127 L/h</b> |
| 50% load PRP  | <b>89 L/h</b>  |

### AIR SYSTEM

|                  |                  |
|------------------|------------------|
| Intake air flow  | <b>963.3 L/s</b> |
| Cooling air flow | /                |

### GENERAL ENGINE DATA

|                                   |                                        |
|-----------------------------------|----------------------------------------|
| Bore × stroke                     | <b>170 × 185 mm</b>                    |
| Displacement                      | <b>25.2 L</b>                          |
| Cooling system                    | <b>Water-cooled</b>                    |
| Lube oil consumption at full load | <b>0.5%-1% of fuel<br/>consumption</b> |
| Compression ratio                 | <b>14.5:1</b>                          |
| Air filter                        | <b>Dry</b>                             |

### EXHAUST SYSTEM

|                               |                   |
|-------------------------------|-------------------|
| Maximum exhaust temperature   | <b>600 °C</b>     |
| Exhaust gas flow              | <b>2573.3 L/s</b> |
| Maximum allowed back pressure | <b>10 kPa</b>     |

### STARTING SYSTEM

|                     |               |
|---------------------|---------------|
| Starting power      | <b>9 kW</b>   |
| Recommended battery | <b>120 Ah</b> |
| Number of batteries | <b>2</b>      |
| Auxiliary voltage   | <b>24 VDC</b> |

### OIL AND COOLING CAPACITIES

|                        |                          |
|------------------------|--------------------------|
| Engine oil capacity    | <b>75 L</b>              |
| Total coolant capacity | <b>55(engine only) L</b> |

# ALTERNATOR DATA

**3-phase · Brushless · Electronic AVR**

## GENERAL ALTERNATOR DATA

|                                |                    |                               |
|--------------------------------|--------------------|-------------------------------|
| Number of phases               | <b>3</b>           | <b>Power factor (Cos Phi)</b> |
| Power factor (Cos Phi)         | <b>0.8</b>         |                               |
| Poles                          | <b>4</b>           |                               |
| Winding connections (standard) | <b>Star-series</b> |                               |
| Insulation                     | <b>H class</b>     |                               |
| Enclosure (IEC 34-5)           | <b>I</b>           |                               |

## GENERAL ALTERNATOR DATA

|                    |                                       |
|--------------------|---------------------------------------|
| Excitation system  | <b>Self-excited, brushless</b>        |
| Voltage regulator  | <b>AVR (Electronic)</b>               |
| Number of bearings | <b>Single bearing</b>                 |
| Coupling system    | <b>Flexible disc</b>                  |
| Coating type       | <b>Standard (vacuum impregnation)</b> |

The alternator is coupled to the engine through a flexible disc on a single-bearing spigot fit. Alternator make and frame size are selected to match the set rating and the site specification, and are confirmed on the quotation.

# CONTROL MODULE

## Automatic Mains Failure (AMF) controller

### AMF CONTROL

Provides automatic mains failure control plus manual or remote start/stop, with generator and mains measurement, protection, event logging and timer functions.

### MOUNTING AND DISPLAY

Panel-mounted controller with back-lit LCD display, push-button interface and LED status indication; sealed front to IP54 for dusty or damp plant rooms.

### CORE FUNCTIONS

- |                                                                                                     |                                                                                            |
|-----------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------|
| <p><b>01</b> Automatic mains failure control plus manual or remote start/stop</p>                   | <p><b>02</b> 3-phase generator and mains voltage measurement, plus current measurement</p> |
| <p><b>03</b> Fully configurable timers, setpoints and alarm protections</p>                         | <p><b>04</b> Detailed event log for fault analysis</p>                                     |
| <p><b>05</b> Engine protection: low oil pressure, high coolant temperature, overspeed, overload</p> | <p><b>06</b> AMF start, cooldown stop and mains return transfer sequences</p>              |
| <p><b>07</b> Front-panel configuration or configuration via PC software</p>                         | <p><b>08</b> Emergency-stop functionality</p>                                              |

The exact controller variant is selected to match the engine communication protocol (J1939 CAN or analogue) and the site specification, and is confirmed on the quotation.

# CONNECTIVITY

## Communication and monitoring options

|     |             |                    |                        |
|-----|-------------|--------------------|------------------------|
| USB | CAN / J1939 | RS485 / MODBUS RTU | ETHERNET / 4G (option) |
|-----|-------------|--------------------|------------------------|

## COMMUNICATION AND MONITORING FEATURES

- 01 USB** Local configuration and firmware updates from a laptop
- 02 CAN / J1939** Direct communication with compatible engine ECUs
- 03 RS485 / MODBUS RTU** SCADA and BMS integration on request
- 04 ETHERNET / 4G (option)** Remote monitoring via web portal or mobile app

## REMOTE MONITORING

Gensets can be monitored on site through the controller display, or remotely through an optional communication module and web-based monitoring portal. Remote start/stop, alarms and running reports are available where the site network allows.

### PLUG-IN MODULES

Ethernet, 4G-GPS or RS232/RS485 modules are ordered with the set; only one module is fitted.